XPSAV11113

module XPSAV - Emergency stop - 24 V DC



Main

Range of product	Preventa Safety automation
Product or component type	Preventa safety module
Safety module name	XPSAV
Safety module application	For emergency stop and switch monitoring
Function of module	Monitoring of a movable guard associated with 2 switches automatic start Emergency stop monitoring 1-channel wiring Emergency stop monitoring 2-channel wiring Emergency stop button with 1 NC contact, automatic start or unmonitored start Emergency stop button with 2 NC contacts, monitored start
Safety level	Can reach SILCL 3 conforming to EN/IEC 62061 Can reach PL e/category 4 conforming to EN/ISO 13849-1
Safety reliability data	PFHd = 7.95E-9 1/h conforming to EN/IEC 62061 MTTFd = 75.8 years conforming to EN/ISO 13849-1 DC > 99 % conforming to EN/ISO 13849-1
Type of start	Configurable
Connections - terminals	Captive screw clamp terminals (2 x 0.52 x 1.5 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (2 x 0.252 x 1 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (2 x 0.142 x 0.75 mm²)solid cable with cable end, with double bezel Captive screw clamp terminals (2 x 0.142 x 0.75 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (1 x 0.251 x 2.5 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (1 x 0.251 x 1.5 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (1 x 0.141 x 2.5 mm²)solid cable with cable end, with double bezel Captive screw clamp terminals (1 x 0.141 x 2.5 mm²)flexible cable with cable end, with double bezel Captive screw clamp terminals (1 x 0.141 x 2.5 mm²)flexible cable with cable end, with double bezel
Output type	Relay time delay opening 3 NO, volt-free Relay instantaneous opening 3 NO, volt-free
Number of additional circuits	3 solid state outputs
[Us] rated supply voltage	24 V DC (- 2020 %)

Complementary

Synchronisation time between inputs	Unlimited for emergency stop	
	1.5 s for guard	
Power consumption in W	<= 5 W DC	
Input protection type	Internal, electronic	
Time delay	Adjustable between 0 to 300 s	
Control circuit voltage	24 V DC	
Line resistance	100 Ohm with cable length: <= 2000 m	
Breaking capacity	C300: 1800 VA, AC-15 (inrush) for relay output	
	C300: 180 VA, AC-15 (holding) for relay output	
Breaking capacity	1.25 A at 24 V (DC-13) time constant: 50 ms for relay output	
	20 mA at 24 V	

Output thermal current	6 A for 1 output and 2 A for the other 2 outputs for instantaneous and time delay	
	outputs 3.3 A for all 3 outputs for instantaneous and time delay outputs	
	2 A for 1 output and 4 A for the other 2 outputs for instantaneous and time delay	
	outputs	
[lth] conventional free air thermal current	20 A	
Associated fuse rating	6 A fuse type fast blow conforming to EN/IEC 60947-5-1, DIN VDE 0660 part 200 4 A fuse type gG or gL for instantaneous and time delay outputs conforming to	
	EN/IEC 60947-5-1, DIN VDE 0660 part 200	
Minimum output current	10 mA for relay output	
Minimum output voltage	17 V for relay output	
Response time on input open	<= 30 ms	
[Ui] rated insulation voltage	300 V (degree of pollution: 2) conforming to IEC 60647-5-1, DIN VDE 0110 part 1	
[Uimp] rated impulse withstand voltage	4 kV overvoltage category III conforming to IEC 60647-5-1, DIN VDE 0110 part 1	
Local signalling	11 LEDs	
Mounting support	35 mm symmetrical DIN rail	
Product weight	0.32 kg	
Environment		
Standards	EN 1088/ISO 14119	


Standards	EN 1088/ISO 14119 EN/IEC 60204-1 EN/IEC 60947-5-1 EN/ISO 13850	
Product certifications	CSA TÜV UL	
IP degree of protection	IP40 (enclosure) conforming to EN/IEC 60529 IP20 (terminals) conforming to EN/IEC 60529	
Ambient air temperature for operation	-1055 °C	
Ambient air temperature for storage	-2585 °C	



Product data sheet Dimensions Drawings

XPSAV11113

Dimensions



XPSAV11113

Wiring Diagrams

Refer to the Instruction Sheet

To download the instruction sheet, follow below procedure:



module XPSAC - Emergency stop - 24 V AC DC

- Click on Download & Documents.
- 2 Click on Instruction sheet.