

ATV31C037N4

enclosed variable speed drive ATV31 - 0.37kW
- 500V - IP55



Main

| | |
|------------------------------------|--|
| Range of product | Altivar 31 |
| Product or component type | Variable speed drive |
| Product destination | Asynchronous motors |
| Product specific application | Simple machine |
| Assembly style | Enclosed |
| Component name | ATV31 |
| EMC filter | Integrated |
| Power supply voltage | 380...500 V (- 15...10 %) |
| Power supply frequency | 50...60 Hz (- 5...5 %) |
| Network number of phases | 3 phases |
| Motor power kW | 0.37 kW |
| Motor power hp | 0.5 hp |
| Line current | 1.7 A for 500 V and 1 kA 2.2 A for 380 V and 1 kA |
| Apparent power | 1.5 kVA |
| Maximum prospective line Isc | 5 kA |
| Maximum transient current | 2.3 A during 60 s |
| Power dissipation in W | 32 W at nominal load |
| Speed range | 1...50 |
| Transient overtorque | 150...170 % of nominal motor torque |
| Asynchronous motor control profile | Factory set : constant torque Sensorless flux vector control with PWM type motor control signal |
| IP degree of protection | IP55 |
| Nominal output current | 1.5 A at 4 kHz |

Complementary

| | |
|-------------------------------|---|
| Power supply voltage limit | 323...550 V |
| Power supply frequency limits | 47.5...63 Hz |
| Speed drive output frequency | 0.5...500 Hz |
| Nominal switching frequency | 4 kHz |
| Switching frequency | 2...16 kHz adjustable |
| Braking torque | 100 % without braking resistor 100 % with braking resistor continuously ≤ 150 % with braking resistor for 60 s |
| Regulation loop | Frequency PI regulator |
| Motor slip compensation | Adjustable Automatic whatever the load Suppressable |
| Output voltage | ≤ power supply voltage |
| Electrical connection | Terminal 2.5 mm ² / AWG 14 Terminal 2.5 mm ² / AWG 14 |
| Tightening torque | AI1, AI2, AI3, AOV, AOC, R1A, R1B, R1C, R2A, R2B, LI1...LI6 0.6 N.m L1, L2, L3, U, V, W, PA, PB, PA+, PC/- 0.8 N.m |
| Insulation | Electrical between power and control |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

| | |
|-------------------------------------|--|
| Supply | Internal supply for logic inputs 19...30 V , > 0...0.1 A for short-circuit protection Internal supply for logic inputs 19...30 V , > 0...0.1 A for overload protection Internal supply for reference potentiometer 10...10.8 V , > 0...0.01 A for short-circuit protection Internal supply for reference potentiometer 10...10.8 V , > 0...0.01 A for overload protection |
| Analogue input number | 3 |
| Analogue input type | AI1 configurable voltage 0...10 V , input voltage 30 V max , impedance 30000 Ohm AI2 configurable voltage +/- 10 V , input voltage 30 V max , impedance 30000 Ohm AI3 configurable current 0...20 mA , impedance 250 Ohm |
| Input sampling time | Analog AI1, AI2, AI3 8 ms Discrete LI1...LI6 4 ms |
| Output response time | Analog AOV, AOC , 8 ms Discrete R1A, R1B, R1C, R2A, R2B , 8 ms |
| Linearity error | +/- 0.2 % for output |
| Analogue output number | 2 |
| Analogue output type | AOC configurable current 0...20 mA , impedance 800 Ohm , resolution 8 bits AOV configurable voltage 0...10 V , impedance 470 Ohm , resolution 8 bits |
| Discrete input logic | LI1...LI4 logic input not wired , state 1 < 13 V LI1...LI6 negative logic (source) , state 0 > 19 V LI1...LI6 positive logic (source) , state 0 < 5 V , state 1 > 11 V |
| Discrete output number | 2 |
| Discrete output type | R1A, R1B, R1C configurable relay logic 1 NO + 1 NC 100000 cycles R2A, R2B configurable relay logic NC 100000 cycles |
| Minimum switching current | R1-R2 10 mA at 5 V DC |
| Maximum switching current | R1-R2 on resistive load, 5 A at 250 V AC, cos phi = 1, L/R = 0 ms R1-R2 on resistive load, 5 A at 30 V DC, cos phi = 1, L/R = 0 ms R1-R2 on inductive load, 2 A at 250 V AC, cos phi = 0.4, L/R = 7 ms R1-R2 on inductive load, 2 A at 30 V DC, cos phi = 0.4, L/R = 7 ms |
| Discrete input number | 6 |
| Discrete input type | LI1...LI6 programmable 24 V , 0...100 mA compatible with PLC , impedance 3500 Ohm |
| Acceleration and deceleration ramps | S, U or customized Linear adjustable separately from 0.1 to 999.9 s |
| Braking to standstill | By DC injection |
| Protection type | Drive short-circuit between motor phases Drive input phase breaks Drive motor phase breaks Drive line supply phase loss safety function, for three phases supply Drive line supply overvoltage and undervoltage safety circuits Drive overcurrent between output phases and earth (on power up only) Drive overheating protection Motor thermal protection |
| Insulation resistance | ≥ 500 MOhm at 500 V DC for 1 minute |
| Local signalling | 1 LED (red) for drive voltage Four 7-segment display units for CANopen bus status |
| Time constant | 5 ms for reference change |
| Frequency resolution | Analog input 0.1...100 Hz Display unit 0.1 Hz |
| Communication port protocol | CANopen Modbus |
| Type of connector | 1 RJ45 for Modbus 1 RJ45 for CANopen via VW3 CANTAP2 adaptor |
| Physical interface | RS485 multidrop serial link for Modbus |
| Transmission frame | RTU for Modbus |
| Transmission rate | 10, 20, 50, 125, 250, 500 kbps or 1 Mbps for CANopen via VW3 CANTAP2 adaptor 4800, 9600 or 19200 bps for Modbus |
| Number of addresses | 1...127 for CANopen via VW3 CANTAP2 adaptor 1...247 for Modbus |
| Number of drive | 31 for Modbus 127 for CANopen via VW3 CANTAP2 adaptor |
| Marking | CE |
| Operating position | Vertical +/- 10 degree |

| | |
|---------------------------------------|---|
| Product weight | 8.8 kg |
| Environment | |
| Dielectric strength | 2410 V DC between earth and power terminals 3400 V AC between control and power terminals |
| Electromagnetic compatibility | 1.2/50 μ s - 8/20 μ s surge immunity test conforming to IEC 61000-4-5 level 3 Electrical fast transient/burst immunity test conforming to IEC 61000-4-4 level 4 Electrostatic discharge immunity test conforming to IEC 61000-4-2 level 3 Radiated radio-frequency electromagnetic field immunity test conforming to IEC 61000-4-3 level 3 |
| Standards | EN 50178 |
| Product certifications | C-Tick CSA N998 UL |
| Pollution degree | 2 |
| Protective treatment | TC |
| Vibration resistance | 1 gn (f = 13...150 Hz) conforming to EN/IEC 60068-2-6 1.5 mm (f = 3...13 Hz) conforming to EN/IEC 60068-2-6 |
| Shock resistance | 15 gn for 11 ms conforming to EN/IEC 60068-2-27 |
| Relative humidity | 5...95 % without condensation conforming to IEC 60068-2-3 5...95 % without dripping water conforming to IEC 60068-2-3 |
| Ambient air temperature for storage | -25...70 °C |
| Ambient air temperature for operation | -10...50 °C without derating with protective cover on top of the drive -10...60 °C with derating factor without protective cover on top of the drive |
| Operating altitude | \geq 1000 m with current derating 1 % per 100 m Without derating |
| RoHS EUR conformity date | 0915 |
| RoHS EUR status | Compliant |